
SECTION 4 – CALL COMPLETION SERVICE

4.1 Call Completion Service (Cont'd)

4.1.3 Provisioning and Description of FGD

FGD is provided as trunk and MF-Pulsing side switching and may be provided with wink start signals and answer and disconnect supervisory signaling. You may also specify out of band signaling.

FGD switching is provided with multifrequency address or out of band signaling. Up to 12 digits of the called party number dialed by the customer's end user using dual tone multifrequency or dial pulse address signals will be provided by TCG to the customer's premises where Call Completion Service terminates. Such address signals are subject to the ordinary transmission capabilities of the Digital Transmission Service provided.

Calls in the terminating direction will not be completed to 950-XXXX access codes, local operator assistance (0- and 0+), Directory Assistance (411 or 555-1212), service codes 611 and 911, or 10XXX access codes.

The access code for FGD switching is a uniform access code of the form 10XXX. A single access code will be the assigned number of all FGD access provided to the customer by TCG. No access code is required for calls to a customer over FGD facilities if the end user's service is arranged for presubscription.

Where no access code is required, the number dialed by the customer's end user shall be a seven or ten digit number for calls in the North America Numbering Plan (NANP), except for 00- dialed calls which are routed to the predesignated customer. For international calls outside the NANP, a seven to twelve digit number may be dialed. The form of the numbers dialed by the customer's end user is NXX-XXXX, 0 or 1 + NXX XXXX, NPA + NXX-XXXX, 0 or 1 + NPA + NXX-XXXX, and where the TCG switch is equipped for International Direct Distance Dialing (IDDD), 01 + CC + NN or 011 + CC +NN.