

PSC NO: 220 ELECTRICITY
NIAGARA MOHAWK POWER CORPORATION
INITIAL EFFECTIVE DATE: APRIL 27, 2009

LEAF: 106
REVISION: 0
SUPERSEDING REVISION:

GENERAL INFORMATION

19. NETWORK AREA SERVICE:

19.1 Electric service in network areas will normally be from a 120/208 volt, 4 wire system.

19.1.1 Service laterals shall be installed as provided in Rule 21.6.

19.1.2 Customer shall submit drawing of service entrance equipment for Company approval prior to construction.

19.1.3 Where Company's service cables exceeds four sets in number, customer's service equipment shall include a service bus on the supply side to which customer will connect his service equipment and to which customer will fasten the Company's service cables.

19.1.4 For large loads in network areas Company may require customer to install vaults or enclosures as specified in Rule 23.

20. NON-NETWORK VOLTAGE IN A NETWORK AREA:

20.1 Non-network, three phase, four wire, 60 cycle, 277/480Y volt service may be supplied by Company upon application from one customer or a group of customers in one building within the area served by Company's 60 cycle networks, subject to the arrangement of supply facilities specified by Company, and provided that:

20.1.1 Such Customer or group of Customers shall take such service on an annual basis and with an aggregate minimum monthly billing demand of not less than 500 kilowatts.

20.1.2 Three phase, four wire, 60 cycle, 277/480Y volt service shall not be combined with service of other characteristics for billing purposes.

20.1.3 Where three phase, four wire, 60 cycle, 277/480Y volt service is supplied to a new building, Company will not thereafter furnish service of other characteristics.

20.1.4 Where three phase, four wire, 60 cycle, 277/480Y volt service is supplied to an existing building, Company will not thereafter increase the capacity of connections used to furnish service of other characteristics.

20.2 Customer shall install the vaults to house Company's transformers and equipment at a location mutually agreed upon and as specified in Rule 23. Sufficient space shall be provided to accommodate additional or larger transformers for future load growth.

20.3 Customer's installation and service equipment shall comply with the applicable provisions of Rule 19.