

Matrix Telecom, LLC  
d/b/a VarTec Telecom  
P.S.C. No. 2 - Telephone  
Effective: November 5, 2018

---

Leaf: 54  
Revision: 0  
Superseding Revision:

## COMPETITIVE ACCESS PROVIDER SERVICES

### SECTION 5 - SWITCHED ACCESS RATES, (CONT'D.)

#### 5.3 Billing of Access Minutes

When recording originating calls over FG Access with multi-frequency address signaling, usage measurement begins when the first wink supervisory signal is forwarded from the Customer's facilities. The measurement of originating call usage over FG Access ends when the originating FG Access entry switch receives disconnect supervision from either the originating End User's Local Switching Center - (indicating that the originating End User has disconnected), or the Customer's facilities, whichever is recognized first by the entry switch.

For terminating calls over FG Access with multi-frequency address signaling, the measurement of access minutes begins when a seizure signal is received from the Carrier's trunk group at the Point of Presence within the LATA. The measurement of terminating call usage over FG Access ends when a disconnect signal is received, indicating that either the originating or terminating user has disconnected.

When recording originating calls over FG Access with SS7 signaling, usage measurement begins with the transmission of the initial address message by the switch for direct trunk groups and with the receipt of an exit message by the switch for tandem trunk groups. The measurement of originating FG Access usage ends when the entry switch receives or sends a release message, whichever occurs first.

For terminating calls over FG Access with SS7 signaling, the measurement of access minutes begins when the terminating recording switch receives the initial address message from the terminating End User. On directly routed trunk groups or on tandem routed trunk groups, the Company switch receives the initial address message and sends the indication to the Customer in the form of an answer message. The measurement of terminating FG Access call usage ends when the entry switch receives or sends a release message, whichever occurs first.

---

Issued By:

Charles Griffin, Chief Executive Officer, 433 East Las Colinas Blvd., Suite 500, Irving, Texas 75039

Cancelled by supplement No. 1 effective 03/05/2023