

PSC NO: 121 ELECTRICITY
NEW YORK STATE ELECTRIC & GAS CORPORATION
Initial Effective Date: 10/17/09

Leaf: 66
Revision: 0
Superseding Revision:

SERVICE CLASSIFICATION NO. 4 (Cont'd.)

SPECIAL PROVISIONS: (Cont'd.)

- b. Be responsible for all engineering design, construction, mapping and maintenance of its facilities. Record keeping shall also be the responsibility of the customer. Notify the Company in writing, 15 business days prior to the completed installation of customer owned equipment, the number of units to be installed, the size, light source, burning hours and wattage of each lamp type. Where applicable, wattage rating shall include load impressed by associated ballast.
- c. Promptly notify the Company of all subsequent lamp installations, removals or replacements. Such notification shall not apply to replacement of lamps with lamps of like type and size.
- d. Provide ownership identification of its equipment which is visible from the ground. In addition, customer shall identify lamp-fixtures in accordance with the latest NEMA Standards for high intensity discharge lamps and luminaires. (NEMA Publication No. OD 150-1977 and subsequent revisions).
- e. Pay, in addition to the connection charges set forth in Special Provision 2h, the Company's costs and expenses to extend its distribution facilities to the designated point(s) of service and, if necessary, any rearrangement of distribution facilities at the point of service. Pole replacements, necessitated by the attachment of customer's facilities, will be billed the customer in accordance with Special Provision 1f.
- f. Extend the street lighting circuits (wires or cables, poles or conduits) to the designated point(s) of service and provide a Company approved in-line disconnecting device equipped with over-current protection as follows:
 - (1) Fixture mounted on an existing Company or jointly owned wood pole - Install supply conductors and a bonding conductor (#6 copper minimum) of sufficient length to reach Company's secondary facilities on the pole, mount the in-line disconnecting device at bracket pole plate and connect the bonding wire to the bracket. The Company will place supply wires and bonding wires above bracket pole plate and make connections to the distribution facilities.
 - (2) Underground supplied fixture fed from Company's overhead distribution facilities - Install an approved 10' riser, to be located by the Company, on pole, provide sufficient supply conductors coiled at top of riser to reach Company's secondary facilities, install an in-line disconnecting device and, if metallic riser is installed, provide appropriate grounds. The Company will place the supply conductors above the riser and make connections to the distribution facilities.
 - (3) Underground supplied fixture fed from Company's underground distribution facilities - Build a pull box within 50' of Company's manhole or handhole designated as the point of service, extend a conduit from customer's pull box to the Company's manhole or handhole, mount the in-line disconnecting device in the pull box and leave sufficient supply conductors (cable) coiled in pull box to reach center of Company's manhole. In addition, customer shall install a 200 lb. nylon pull cord in conduit section so that Company can draw in customer's cable. (If customer elects to install an approved direct buried cable, the cable should be left coiled and protected at the outside wall of the Company's manhole or handhole). The Company will locate the point of entry for the customer and the Company will provide entry into manhole and make all connections.

If a customer elects to feed a single fixture which is within 50' of the Company's manhole or handhole, the customer's pull box may be eliminated providing there is adequate space in the pole base to mount the in-line disconnecting device and coil cable sufficient to reach Company's manhole or handhole.

Issued by: James A. Lahtinen, Vice President - Rates & Regulatory Economics, Binghamton, NY