

PSC No: 20 - Electricity  
Rochester Gas and Electric Corporation  
Initial Effective Date: June 1, 2003

Leaf No. 65  
Revision: 0  
Superseding Revision:

## GENERAL INFORMATION

### PART II - RULES AND REGULATIONS

#### 6. EXTENSION AND MAINTENANCE OF DISTRIBUTION PROVIDER FACILITIES (Cont'd)

**D. PLURALITY OF SERVICES (Cont'd)**

When the Distribution Provider elects to supply the Retail Customer's premises through more than one service connection of a single type of current, the energy (kWh) and the noncoincident monthly maximum demands (kW) for each service connection will be added for billing, unless the expense for wiring and additional meter equipment necessary for the measurement of coincident demands is borne by the Distribution Customer.

**E. METER**

1) General

Except for unmetered services as provided for in Rule 3.B.(2), the Distribution Provider or a competitive Meter Service Provider (MSP) will furnish and install the meter or meters to measure the electricity used by the Retail Customer in accordance with the provisions of Schedule A. Such meter or meters shall be installed on the Retail Customer's side of the point of supply. Meters installed by the Distribution Provider shall remain the property of the Distribution Provider, except as provided for in Rule 3.B and Rule 11.C. The Retail Customer shall protect the meter and furnish sufficient and proper space for its installation. The Retail Customer shall continually maintain a safe and clear approach to any Distribution Provider owned meter or, if such an approach cannot be maintained, the Distribution Customer shall bear the expense of the relocation of the meter and relocation of the service lateral, or any portion thereof, to a more suitable location to be mutually agreed upon by the Distribution Provider and the Distribution Customer. Such relocation will be performed by the Distribution Provider. A service panel in accordance with the specifications of the Distribution Provider is required.

Meters shall be installed outside, whenever feasible, for all new one-, two- and three-family houses. A remote meter reading device shall be installed for all new one-, two- and three-family houses where an outside meter installation is not feasible. The Distribution Customer shall pay to the Distribution Provider its costs and expenses, for the remote meter reading device and its installation.

The costs and expenses of the meter enclosure and socket shall be borne by the Distribution Customer. All meter enclosures and sockets must be approved by and may be purchased from the Distribution Provider. For metering installations which require instrument transformers to be included as part of the meter enclosure, the meter enclosure must be approved by, and purchased from, the Distribution Provider.

At the request of a Distribution Customer, a remote meter reading device may be installed for an existing inside meter. The Distribution Customer shall pay to the Distribution Provider the cost of the remote meter reading device and its installation.

(Continued on next leaf)

ISSUED BY: James A. Lahtinen, Vice President Rates and Regulatory Economics, Rochester, New York