

PSC NO: 10 – Electricity  
Consolidated Edison Company of New York, Inc.  
Initial Effective Date: 02/01/2017  
Issued in compliance with Order in Cases 16-E-0060 and 16-E-0196 dated 1/25/2017

Leaf: 157.3  
Revision: 4  
Superseding Revision: 2

## GENERAL RULES

### 20. Standby Service - Continued

#### 20.2 Interconnection and Operation - Continued

##### 20.2.1 – Continued

##### (B)(8) – Continued

##### (e) Billing Applicable to Each Account Supplied by the Generating Facility's Output:

- (1) Allocated As-used Generator Demand and Allocated Generator Supply will be determined for each 15-minute interval. Adjustments will be made for transformation losses as applicable. For purposes of this General Rule, the following definitions apply:

##### For Accounts Supplied Under the Single Party Offset

“Allocated As-used Generator Demand” means, for each account supplied by the generating facility's output, the demand registered on the account's meter(s) multiplied by the lower of: (a) 1 or (b) the ratio of the demand registered on the high-tension meter(s) measuring the generating facility's output to the sum of demands registered on the meters of all Standby Service accounts supplied by the generating facility's output.

“Allocated Generator Supply” means, for each account supplied by the generating facility's output, the total kilowatt-hours registered on the account's meter(s) multiplied by the lower of: (a) 1 or (b) the ratio of the total kilowatt-hours registered on the high-tension meter(s) measuring the generating facility's output to the sum of the kilowatt-hours registered on the meters of all Standby Service accounts supplied by the generating facility's output.

##### For Accounts Supplied Under the Multi-party Offset

“Allocated As-used Generator Demand” means, for each Recipient Account, the lower of (a) the demand registered on the Recipient Account or (b) the demand registered on the high-tension meter(s) measuring the generating facility's output multiplied by the Recipient Account's Percentage Allocation. If the generating facility's output multiplied by the Recipient Account's Percentage Allocation exceeds the demand registered on the Recipient Account, the excess amount shall neither be redistributed to other accounts nor carried forward to the succeeding billing period.

“Allocated Generator Supply” means, for each Recipient Account, the lower of (a) the total kilowatt-hours registered on the Recipient Account's meter(s) or (b) the total kilowatt-hours registered on the high-tension meter(s) measuring the generating facility's output multiplied by the Recipient Account's Percentage Allocation. If the generating facility's output multiplied by the Recipient Account's Percentage Allocation exceeds the kilowatt-hours registered on the Recipient Account's meter(s), the excess amount shall be credited to the extent described in General Rule 20.2.1(B)(8)(a)(7).

Issued by: Robert Hoglund, Senior Vice President & Chief Financial Officer, New York, NY